

# ScreenPRO-II Controller with tally

ScreenPRO-II Controller allows users to remotely operate up to four ScreenPRO-II seamless switchers. The controller interfaces with each ScreenPRO-II individually, or as a group.



## Product specifications

## SCREENPRO-II CONTROLLER WITH TALLY

General specifications	
Video Routing	Input capability: Up to 16 input sources Output destinations: 1-4 ScreenPRO II processors External router Control: Up to 3 External Routers: 1 Analog, 1 SDI/ HDSDI, 1 DVI
Operator Control	Display: 3.8" LCD Touch Screen Joystick: 3-Axis (X,Y and Z) T-Bar: Analog T-Bar with smooth movement Presets: 36 (6 pages of 6 Presets) Destinations: 8 Total Destinations (4 ScreenPRO II and 4 AUX)
Control/Remote	Ethernet: 1 RJ-45 (F) connector, running 10/100 Base-T, half/full duplex w/ auto detect Ethernet Protocol: ICMP (ping), TCP/Ethernet Protocol CP/IP, Telnet Serial Control Ports: 2-RS-232 ports, each 9-pin female D connector Baud rate and Protocol: 115K Baud, 8-bit, 1 stop, no parity selectable Keyboard Port (Optional): PS/2 Connector Tally (Optional): DB-25 Male, Dry-Contact Relay Closures: 1 Amp at 30 VDC, .5 Amps at 125 VDC Backup option: Removable Media Card, Type 1 Compact Flash Compliant
Enclosure	Dimensions: 5.95" H X 17.0" W X 10" D (2U high, full rack width) 15.13cm H X 43.2 cm W X 25.4 cm D Weight: 12 lbs (5.45 kg) Console Light: XLR type Connector
Environmental	Temperature: 0-40° C Environmental Humidity: 0-95%, non-condensing Power Type: 100-240 VAC – 50/60 Hz. Auto Selecting 1.0A Max
Remote Programming	Serial Control Port: RS-232, 9Pin Female D connector Baud rate and Protocol: 115kb/sec, 8-bit, 1 stop bit, no parity selectable

Last updated: 15 Mar 2023

© 2018 Barco nv. All rights reserved. Reproduction in whole or in part without written permission is prohibited. All brand names and product names are trademarks, registered trademarks or tradenames of their respective holders. Due to continued innovation, information and technical specifications are subject to change without prior notice. Please check [www.barco.com](http://www.barco.com) for the latest specifications.